

## EL2211 系列

10/100/1000BASE-TX - 1000BASE-SX/LX/BX光電轉換器

image not found or type unknown



### 產品介紹

EL2211系列提供10/100/1000BASE-TX與1000BASE-SX/LX/BX光電轉換；透過DIP Switch指撥器，可以開關LFPT功能,能針對光電轉換器連線狀態提供持續有效的監控。

EL2211採散熱性極佳的鋁製外殼設計，可支援0°C到50°C寬溫操作，提供Gigabit高速傳輸速率，支援9K bytes Jumbo Frame,可壁掛或搭配益網

[EMC1600](#)(19吋標準機箱)集中收容管理。

EtherWAN — "When Connectivity is Crucial."

## 產品亮點

### + 支援全Gigabit頻寬及Jumbo frames

10/100/1000BASE-TX 和 1000BASE-SX/LX/BX 乙太網信號自動轉換

1000Mbps 全雙工，10/100Mbps 全/半雙工。

### + 可搭配多埠型光電轉換器收容箱使用

可支援壁上安裝或EtherWAN EMC1600 chassis收容式機箱安裝並支援雙備援電源輸入

### + 支援Link-Fault-Pass-Through (LFPT)

針對光電轉換器連線狀態提供持續的監控

當連線的其中一端光纖中斷訊，LFPT會中斷乙太網路(RJ-45)埠之連線，以告知連線之設備網路連線已中斷

## 產品規格

### + 介面

#### 乙太網路埠

10/100/1000BASE-TX: 1 port

1000BASE-SX/LX/BX: 1 port

#### LED 指示燈號

Per Unit: Power, LFPT

Per Port: Link/Activity, Speed

### + 技術

#### 標準

IEEE 802.3 10BASE-T

IEEE 802.3u 100BASE-TX

IEEE 802.3ab 1000BASE-T

IEEE 802.3z 1000BASE-SX/1000BASE-LX

IEEE 802.3x Full duplex and flow control

#### Forward/Filtering Rate

14,880pps for 10Mbps

148,810pps for 100Mbps

1,488,100pps for 1000Mbps

#### 傳輸型式

Store-and-forward

Half-duplex back-pressure and IEEE 802.3x full-duplex flow control

Auto-negotiation

Auto MDI/MDIX

### + 電源

#### 輸入電壓

12VDC

**電力功耗**

2.76W max. 0.23A@12VDC

**+ 機構****機殼**

Aluminum

**尺寸**

80.3 x 109.2 x 23.8mm (W x D x H)

3.16" x 4.30" x 0.94"

**重量**

0.15kg (0.33lbs)

**安裝方式**

Wall mounting, or in EMC1600 Chassis System

**+ 環境****工作溫度**

0 to 50°C (32 to 122°F)

**儲存溫度**

-10 to 70°C (-14 to 158°F)

**工作濕度**

5% to 95% (無凝結)

**+ 通過認證****ISO**

Manufactured in ISO-9001 facility

**Safety**

UL 60950-1

**Emission Compliance**

CE Mark Class A

FCC Part 15B Class A

VCCI Class A

**+ 保固****Length**

Limited Lifetime

**Details**

[www.etherwan.com/support/warranty-policy](http://www.etherwan.com/support/warranty-policy)

**+ What's Included****Device**

Media Converter


**Power**

12VDC Power Adapter


**Documentation**

Quick Install Guide

## 產品應用圖



## 產品尺寸圖



## 訂購型號

### + 型號

**EL2211-X1Z** 10/100/1000BASE-TX to 1000BASE-X Media Converter

Note: Shipment comes along with universal adapter; US (JP) /EU/UK plugs are included.

### + Gigabit Port Options (X)

- 3** 1000BASE-SX (SC) - 550m (850nm)
- 4** 1000BASE-SX (SC) - 2Km (1310nm)
- 5** 1000BASE-SX (ST) - 550m (850nm)
- A** 1000BASE-LX (SC) - 10Km
- B** 1000BASE-LX (SC) - 20Km (1310nm)
- E** 1000BASE-LX (SC) - 40Km (1310nm)
- R** 1000BASE-BX (SC) WDM-TX: 1310nm/RX: 1550nm-20Km
- S** 1000BASE-BX (SC) WDM-TX: 1550nm/RX: 1310nm-20Km

### + Power Adapter Options (Z)

- A** with external power adapter for AU
- E** with external power adapter for EU
- J** with external power adapter for JP
- K** with external power adapter for UK
- U** with external power adapter for USA
- 3C** with external power adapter for China

### + Accessories

**Multiple Channel Chassis** [www.etherwan.com/products/media-converters/multiple-channel-media-converters](http://www.etherwan.com/products/media-converters/multiple-channel-media-converters)

